

Attorney Docket No. 02075/TL

**IN THE UNITED STATES PATENT
AND TRADEMARK OFFICE**

Applicant(s): Alois BIEBL
Serial No. : To be assigned
Filed : Concurrently
herewith
For : DRIVE CIRCUIT FOR
AN LED ARRAY
Art Unit :
Examiner :

PRELIMINARY AMENDMENT

Asst. Commissioner for Patents
Washington, D.C. 20231

S I R :

Please amend the above-identified application as follows
(with changes being shown on the attachments hereto):

IN THE SPECIFICATION

Page 1, replace the heading "Technical Field" with
--Field of the Invention--;

replace the heading "Prior Art" with
--Background of the Invention--.

Page 4, replace paragraph 3, corresponding to page 4, line
35 to page 5, line 2 as follows:

One object of the present invention is to provide
a drive circuit for an LED array that ensures
continuing operation of the LED array with a
cost-effective implementation if the entire luminance
of the LED array lies above a prescribable value.

Express Mail Mailing Label
No.: EV 044 466 082 US
Date of Deposit: February 12, 2002

I hereby certify that this paper is being
deposited with the United States Postal Service
"Express Mail Post Office to Addressee" service
under 37 CFR 1.10 on the date indicated above and
is addressed to the Asst. Commissioner for
Patents, Washington, D.C. 20231


Julie Harting

In the event that this Paper is late filed, and
the necessary petition for extension of time is
not filed concurrently herewith, please consider
this as a Petition for the requisite extension of
time, and to the extent not tendered by check
attached hereto, authorization to charge the
extension fee, or any other fee required in
connection with this Paper, to Account
No. 06-1378.

20074131 02075/TL

Page 5, replace paragraph 1, corresponding to page 5, lines 4-7 as follows:

This and other objects are attained by a drive circuit having the features of patent claim 1, and by a method for operating an LED array having the features of patent claim 17.

Page 5, replace paragraph 2, corresponding to page 5, lines 9-32 as follows:

The point of departure is a patent application of the present applicant entitled "Ansteuerschaltung für LED und zugehöriges Betriebsverfahren" ["Drive circuit for LEDs and associated method of operation"] (application No. DE19950135.1; Biebl), in the case of which a plurality of LED clusters are operated in a cascade arrangement. In this case, a higher-level LED cluster is denoted as master cluster, and its average current is fed to a control loop, the drive signal of the master cluster also being used to drive a plurality of lower-level LED clusters, what are termed slave clusters. Starting from the teaching of the application just mentioned, the above object of the invention can be achieved when the total current through all the slave clusters is measured and this current is compared against a prescribable desired value. No fault message is generated as long as the total current lies above the threshold value despite failure of individual slave clusters. A fault signal is not generated until the prescribed threshold value is undershot, which is the same as saying, for example, that the diminished luminance now no longer corresponds to the statutory stipulations.

Page 10, replace the heading "Description of the drawings" with --Brief Description of the Drawings--.

Page 11, after line 1 insert the heading --Detailed Description of the Drawings--.

IN THE ABSTRACT

Replace the Abstract with the following:

Abstract of the Disclosure

A drive circuit for an LED array which comprises a first LED cluster (40) and at least one second LED cluster (42; 44), the switch (S1, S2, S3) being arranged in series with each LED cluster (40, 42, 44), and each LED cluster (40, 42, 44) having a supply terminal. A control loop (46) is designed to drive the switch (S1) of the first LED cluster (42) so as to achieve a constant mean value of the current (I_{LED}) flowing through the first LED cluster (42), the control loop (46) being designed for also driving the switches of the further LED clusters (42, 44). The drive circuit also comprises a total current detection device (R_{Mess}) with the aid of which it is possible to determine an actual magnitude (U_{Mess}) which corresponds to the sum of the currents through at least two, in particular through all of the second LED clusters (42, 44). A comparison unit (50) compares the actual magnitude (U_{Mess}) with a predefinable desired magnitude (U_{OL}).

IN THE CLAIMS

Amend claims 3, 4, 7, 9, 10 and 12-15, as follows.

3. (Amended) The drive circuit as claimed in claim 1, characterized in that the comparison unit (50, 50a) is designed to output an information signal (78) in the event of

undershooting of the desired magnitude (U_{OL}) by the actual
magnitude (U_{Mess}).

4. (Amended) The drive circuit as claimed in claim 1,
characterized in that it comprises a monitoring unit (50, 50b),
with which the current flow through the first LED cluster (40)
can be monitored.

7. (Amended) The drive circuit as claimed in claim 1,
characterized in that it also comprises an undervoltage detection
device (64) which is designed to output an undervoltage warning
signal (76) when the supply voltage (U_{Batt}) falls below a
prescribable value (U_{Ref1}).

9. (Amended) The drive circuit as claimed in claim 7,
characterized in that the prescribable value (U_{Ref1}) can be set
manually or can be prescribed permanently.

10. (Amended) The drive circuit as claimed in claim 3,
characterized in that it also comprises an output unit (50, 50c,
ST1) to which the information signal (78) and/or the undervoltage
warning signal (76) can be transmitted.

12. (Amended) The drive circuit as claimed in claim 1,
characterized in that it also comprises a closing delay device
(74) which is designed to deactivate the output unit (50, 50c,
ST1) for a predetermined time after the closure of the drive
circuit.


13. (Amended) The drive circuit as claimed in claim 10,
characterized in that the output unit (50, 50c, ST1) comprises a
flip-flop (88), the base of the transistor (ST1) being connected
to the output of the flip-flop (88), and the set input (S) of the
flip-flop (88) being connected to the undervoltage detection
device (64) in order to transmit the undervoltage warning signal

(76), and/or being connected to the comparison unit (50a) in order to transmit the information signal (78).

14. (Amended) The drive circuit as claimed in claim 12, characterized in that the closing delay device (74) is designed to apply a closing delay signal (80) to the reset input (R) of the flip-flop (88) of the output unit (50, 50c, ST1) over the duration of the closing delay.

15. (Amended) The drive circuit as claimed in claim 1, characterized in that the actual magnitude (U_{Mess}) corresponds to a time average value of the sum of the currents through at least two, in particular through all of the second LED clusters (42, 44).

Respectfully submitted,


Thomas Langer
Reg. No. 27,264

Frishauf, Holtz, Goodman, Langer & Chick, P.C.
767 Third Avenue - 25th Floor
New York, New York 10017-2023
Tel. No. (212) 319-4900
Fax No. (212) 319-5101
TL/jh

ATTACHMENT

3. (Amended) The drive circuit as claimed in claim 1 [or 2], characterized in that the comparison unit (50, 50a) is designed to output an information signal (78) in the event of undershooting of the desired magnitude (U_{OL}) by the actual magnitude (U_{Mess}).

4. (Amended) The drive circuit as claimed in [one of the preceding claims] claim 1, characterized in that it comprises a monitoring unit (50, 50b), with which the current flow through the first LED cluster (40) can be monitored.

7. (Amended) The drive circuit as claimed in [one of the preceding claims] claim 1, characterized in that it also comprises an undervoltage detection device (64) which is designed to output an undervoltage warning signal (76) when the supply voltage (U_{Batt}) falls below a prescribable value (U_{Ref1}).

9. (Amended) The drive circuit as claimed in [one of claims 7 or 8] claim 7, characterized in that the prescribable value (U_{Ref1}) can be set manually or can be prescribed permanently.

10. (Amended) The drive circuit as claimed in [one of claims 3 to 9] claim 3, characterized in that it also comprises

an output unit (50, 50c, ST1) to which the information signal (78) and/or the undervoltage warning signal (76) can be transmitted.

12. (Amended) The drive circuit as claimed in [one of the preceding claims] claim 1, characterized in that it also comprises a closing delay device (74) which is designed to deactivate the output unit (50, 50c, ST1) for a predetermined time after the closure of the drive circuit.

13. (Amended) The drive circuit as claimed in [one of claims 10 to 12] claim 10, characterized in that the output unit (50, 50c, ST1) comprises a flip-flop (88), the base of the transistor (ST1) being connected to the output of the flip-flop (88), and the set input (S) of the flip-flop (88) being connected to the undervoltage detection device (64) in order to transmit the undervoltage warning signal (76), and/or being connected to the comparison unit (50a) in order to transmit the information signal (78).

14. (Amended) The drive circuit as claimed in [one of claims 12 or 13] claim 12, characterized in that the closing delay device (74) is designed to apply a closing delay signal (80) to the reset input (R) of the flip-flop (88) of the output unit (50, 50c, ST1) over the duration of the closing delay.

15. (Amended) The drive circuit as claimed in [one of the preceding claims] claim 1, characterized in that the actual magnitude (U_{Mess}) corresponds to a time average value of the sum of the currents through at least two, in particular through all of the second LED clusters (42, 44).

Patent-Treuhand-Gesellschaft
für elektrische Glühlampen mbH., Munich

Drive circuit for an LED array

5

~~Technical field~~

Field of the Invention

10 The present invention relates to a drive circuit for an LED array which comprises a first LED cluster and at least one second LED cluster, a switch being arranged in series with each LED cluster, and each LED cluster having a supply terminal via which it can be connected to a supply voltage, it being possible to drive each switch so as to permit a current flow in the associated
15 LED cluster, having a control loop which is designed to drive the switch of the first LED cluster so as to achieve a constant mean value of the current flowing through the first LED cluster, the control loop being designed to drive at least one switch of a second LED
20 cluster. It relates, moreover, to a method for operating an LED array which comprises a first LED cluster and at least one second LED cluster, a switch being arranged in series with each LED cluster, and each LED cluster having a supply terminal via which it
25 can be connected to a supply voltage.

~~Prior art~~

Background of the Invention

30 The invention is concerned with driving LEDs. It is normal for this purpose to use series resistors or current sources which limit and/or control the current through the LED. The LEDs are generally interconnected to form a cluster, that is to say a cluster comprises a series circuit of a plurality of LEDs. A plurality of
35 LED clusters must be connected in parallel, that is to say be combined to form an array, depending on the size of the area to be lit or backlit. There is the basic problem here that a status terminal of the drive circuit is intended to supply a corresponding

10074121-021200

dashes, for further blocks to be part of the same LED array.

The problem with this solution is, firstly, the additional outlay for a counter 28 and a multiplexer 30 and, on the other hand, the fact that a plurality of LED driver blocks are required in the case of larger LED arrays, since the number of current control loops per LED driver block is limited, for example to eight. The use of a plurality of LED driver blocks is reflected, in turn, disadvantageously in the price.

In addition to the disadvantages mentioned, in the case of the solutions addressed there is a further disadvantage that a fault signal is output immediately as soon as a fault has occurred. This is necessary, however, only if, as in the case of the first named solution, the complete LED cluster has failed. With regard to specific fields of application of LED arrays, for example in the vehicle sector as taillights, this would again justify the use of an incandescent bulb. In the case of an incandescent bulb, there also exists only two states of incandescent bulb intact and incandescent bulb not intact. The advantage of using LEDs in this sector resides, however, in the fact that in the event of failure of an LED cluster the light is capable of continuing to be operated if sufficient other functioning LED clusters are still present - although with somewhat diminished luminance - but, if suitably dimensioned, still above a limiting value prescribed by statute.

Summary of the invention

35 ^{one} [The] ^{is to provide a} object of the present invention ^{therefore} consists in developing the ^{drive circuit} [named at the beginning] for an LED array [in such a way that the further] ^{that} ensures ^{continuing} operation of the LED array [is ensured in conjunction] with a cost-effective ^{realization} if the entire ^{implementation}

luminance of the LED array lies above a prescribable value.

and other objects are attained
This [problem is solved] by a drive circuit having the
5 features of patent claim 1, and by a method for
operating an LED array having the features of patent
claim 17.

10 The point of departure is a patent application of the
present applicant entitled "Ansteuerschaltung für LED
und zugehöriges Betriebsverfahren" ["Drive circuit for
LEDs and associated method of operation"] (application
No. DE19950135.1; Biebl [not yet laid open]), in the
15 case of which a plurality of LED clusters are operated
in a cascade arrangement. In this case, a higher-level
LED cluster is denoted as master cluster, and its
average current is fed to a control loop, the drive
signal of the master cluster also being used to drive a
20 plurality of lower-level LED clusters, what are termed
slave clusters. Starting from the teaching of the
application just mentioned, [the finding of the
invention consists in that] the above object ^{of the invention} can be
achieved when the total current through all the slave
25 clusters is measured and this current is compared
against a prescribable desired value. No fault message
is generated as long as the total current lies above
the threshold value despite failure of individual slave
clusters. A fault signal is not generated until the
30 prescribed threshold value is undershot, which is the
same as saying, for example, that the diminished
luminance now no longer corresponds to the statutory
stipulations.

35 This realization offers the advantage that the entire
LED array can be operated despite failure of individual
LED clusters, that the fault detection logic circuit
can be kept very simple, in particular need be provided
only once, and, finally, that the LED array with an
arbitrary number of LED clusters can be monitored by

10074421.02102

clusters is measured as actual magnitude, the actual magnitude subsequently being compared with a prescribable desired magnitude.

5 *Brief* Description of the drawings

Further advantageous embodiments are defined in the subclaims. Exemplary embodiments of the invention are described below in more detail with reference to the
10 attached drawings, in which:

figure 1 illustrates a circuit arrangement, known from the prior art, for driving an LED cluster with pulsed current control;

15 figure 2 illustrates a drive circuit, known from the prior art, for a plurality of LED clusters with a multiplexer;

20 figure 3 illustrates a first exemplary embodiment of a drive circuit according to the invention with detection of the total current of the slave clusters;

25 figure 4a illustrates the characteristic of the fault signal in the event of occurrence of a fault of decisive importance;

figure 4b illustrates the time characteristic of the
30 voltage U_{Mess} in the event of failure of individual LED clusters in the exemplary embodiment of figure 3;

figure 5 shows a detailed illustration of the
35 embodiment of figure 3; and

figure 6 shows a schematic illustration of a block diagram of an embodiment of the fault diagnosis for a drive circuit according to

2004434-031302

the invention.

Detailed Description of the Drawings

Identical reference symbols are used throughout below for identical and equivalent elements of the various
5 exemplary embodiments.

In the drive circuit illustrated in figure 3, a first LED cluster 40 with two LEDs D1, D2 is denoted as master cluster. A plurality of second LED clusters 42,
10 44 with LEDs D3, D4, D5, D6 are denoted as slave clusters. Of course, a multiplicity of LEDs can be arranged per cluster instead of the two LEDs shown by way of example. This is limited essentially by whether the battery voltage U_{Batt} used for the supply suffices
15 in order to apply the sum of the LED forward voltages.

The current flow through the master cluster 40 is detected by means of a resistor R_{Shunt} , the voltage U_{Shunt} dropping across the resistor R_{Shunt} being fed to an LED
20 drive circuit 46. The latter supplies the drive clock pulse CLK for the switch S1 of the master cluster 40, as well as for the switches S2, S3 of the slave clusters 42 and 44. The total current through the slave clusters is determined via a resistor R_{Mess} , the voltage
25 U_{Mess} dropping across the resistor R_{Mess} being fed to the diagnosis unit 50. The latter continues to receive the battery voltage U_{Batt} as well as a signal 48 fed by the LED drive unit 46. The diagnosis unit 50 for its part supplies a signal 58 to the LED drive unit 46. The
30 signals 48 and 58 are described further below in yet more detail, as is the design of the diagnosis unit 50. The output signal of the diagnosis unit 50 is applied to the base of a status transistor ST1 in an open collector circuit. An item of information on the status
35 of the LED array is provided at a collector of the transistor ST1.

Figure 4b shows the time characteristic of the voltage U_{Mess} dropping across the resistor R_{Mess} . Also plotted is

20250724121.021202

Abstract of the Disclosure

[The present invention relates to a ^Adrive circuit for an LED array which comprises a first LED cluster (40) and at least one second LED cluster (42; 44), the switch (S1, S2, S3) being arranged in series with each LED cluster (40, 42, 44), and each LED cluster (40, 42, 44) having a supply terminal. A control loop (46) is designed to drive the switch (S1) of the first LED cluster (42) so as to achieve a constant mean value of the current (I_{LED}) flowing through the first LED cluster (42), the control loop (46) being designed for also driving the switches of the further LED clusters (42, 44). The drive circuit also comprises a total current detection device (R_{Mess}) with the aid of which it is possible to determine an actual magnitude (U_{Mess}) which corresponds to the sum of the currents through at least two, in particular through all of the second LED clusters (42, 44). A comparison unit (50) compares the actual magnitude (U_{Mess}) with a predefinable desired magnitude (U_{OL}).

[(Figure 3)]

2023-11-20 14:44:00